

ENDON®

Renner 6-Light Flush Fitting INSTRUCTION MANUAL

Safety Warnings

- This product is only suitable for connection to a 240V~50Hz supply in accordance with current IEE wiring Regulations and should be installed in accordance with local Building Regulations and is for Domestic indoor ceiling use only and not suitable for a Bathroom location.
- The light fitting should be connected to a lighting circuit protected by a 5 amp fuse (or a 6 amp miniature circuit breaker).
- This product is a Class I fitting and **must** be Earthed.
- If in doubt we recommend you contact a qualified electrician. Before installing your light fitting always switch off the mains supply and remove the appropriate fuse or switch off the appropriate circuit breaker before commencing installation, and ensure that no one else has access that would enable the supply to be inadvertently reconnected.
- Never fit bulbs of a higher wattage or of a type other than those specified on the label as this may cause overheating and damage the fitting.
- These product contains glass parts – be careful during handling and maintenance to avoid breakage.
- If any modification is made it will invalidate the warranty and may render the product unsafe.

Care Information

Allow 10 minutes to cool before replacing, adjusting or cleaning.
Clean with a dry cloth only. Do not use liquid or abrasive cleaners on this product.

Assembly/ User Instructions

Before you start

Please read these instructions carefully before fitting and retain for reference. Check the packaging and make sure that you have all the required parts. Follow each assembly step in order to prevent incorrect assembly. Ensure that the product is fully assembled as illustrated before use.

This type of Light Fitting may be connected to a Dimmer if a Tungsten incandescent bulb is used. If a CFL/LED type bulb is fitted then these cannot (generally) be controlled by a dimmer.

The Light pack contains:

Light fitting.
Terminal connection block(s).
Fixing pack.
Glass plate.
Decorative drops.

The following tools may be required:

Selection of cross and flat head screwdrivers.
Electric drill and assorted drill bits.
Wire strippers.
Electrical insulation tape.

These assembly diagrams are intended as a guide – if in doubt consult a qualified electrician.

1. Decide on the position of the light fitting, or remove existing light fitting. Take a note of the position of the electrical connections. Ensure there is a solid mounting surface, preferably a wooden joist or joist bridge to support the weight of the light fitting.
2. Remove the fixing bracket by undoing the 2 side screws (3), retain for re-use.
3. Use the fixing bracket as a template to mark the screw holes, mark the screw holes and secure to the ceiling with the fixings (1) supplied.
4. Slide the glass plate (4) over the body of the fitting so it rests on the lip, and secure in place with the metal tab and screw (5)

Assembly/ User Instructions Continued

- Support your fitting and connect the house wiring to the terminal block (2) – see wiring details. **NOTE: This is a Class I fitting and must be earthed.** The 4th terminal block connector is used for the “loop” wires of the “Ring Circuit”. There may be more than one set of cables in the “loop” connections. **If there is a “Ring Circuit” and you do not understand the connections you must consult an electrician.** Any loose terminal blocks –not secured to ceiling cup - should always be covered with 2 layers of good quality insulation tape.
- Secure the fitting back onto the fixing bracket with the 2 side screws (3), removed in 2 above. Make sure that all the internal cables and connections are inside the ceiling cup taking care not to trap or strain the internal cables.
- Fit the decorative drop assemblies (6-8) as shown.
- Fit the bulbs (9) into the lamp holders being careful not to touch the bulbs with your bare hands – use a cloth or gloves to insert the bulbs. **NOTE: Never fit bulbs of a higher wattage or of a type other than those specified on the label (as these may cause overheating and damage the fitting).**
- Turn on the power and test.

