



#### **Function description**

Extremely bright, robust and vigilant: the sensor-switched floodlight. On-demand light for illuminating large areas around buildings. Infrared sensor with 240° angle of coverage and 12 m reach. Light output 1486 lm, colour temperature 4000 K, power consumption 14,7 W. Robust aluminium floodlight head. Available in black or white.

#### **Technical specifications**

Dimensions (L x W x H)	176 x 155 x 210 mm	Electronic scalability	No
With lamp	Yes, STEINEL LED system	Mechanical scalability	No
With motion detector	Yes	Reach, radial	r = 3.5 m (26 m <sup>2</sup> )
Manufacturer's Warranty	3 years	Reach, tangential	r = 12 m (302 m <sup>2</sup> )
Settings via	Potentiometers	Cover material	shrouds
Version	black	Luminous flux total product	1375 lm
PU1, EAN	4007841052546	Measured luminos flux (360°)	1486 lm
Application, place	Outdoors	Total product efficiency	94 lm/W
A sultanting as an	outdoors, all round the building, courtyard & driveway	Colour temperature	4000 K
Application, room		Colour variation LED	SDCM3
Colour	black	Lamp	LED cannot be replaced
Includes corner wall mount	No	Service life LED L70B50 (25°)	> 36000 h
Installation site	wall, corner	Soft light start	No
Installation	Wall, corner, Surface wiring	Twilight setting	2 – 1000 lx
Impact resistance	IK03	Time setting	10 s – 15 Min.
IP-rating	IP44	Basic light level function	No
Protection class		Main light adjustable	No

### https://www.steinel.de

Subject to technical modifications

11.2022 Page 1 from 3



## **Technical specifications**

Ambient temperature	-10 - 40 °C
Housing material	Aluminium
Cover material	Glass transparent
Mains power supply	220 – 240 V / 50 – 60 Hz
Mounting height max.	4,00 m
Sneak-by guard	Yes

Interconnection	No
Output	14,7 W
Colour Rendering Index CRI	= 80
Optimum mounting height	2 m
Detection angle	240 °


# Accessories

EAN 4007841 630560


Corner wall mount LS 150 S



### **Detection Zone**



**Dimension Drawing** 



Mögliche Montagehöhe: 1,80 m – 4,00 m Orange: radial Schwarz: tangential

## Circuit diagram

